

## Add-on Card AOC-S3008L-L8e / AOC-S3008L-L8e+

### Specifications


#### Add-on Card

#### Supermicro 12Gb/s Eight-Port SAS Internal Host Bus Adapter

The Supermicro HBA **AOC-S3008L-L8e** features 8 internal SAS connectors for high-performance storage connectivity.

Use a Broadcom 3008 I/O processor with Fusion-MPT (Message Passing Technology) for optimum performance and a PCI Express host interface for increased bandwidth.

The **AOC-S3008L-L8e** supports 122 devices as a HBA in IT mode.



This product is only available through Supermicro.

**Compatible with Supermicro motherboards only.**

#### Compliance

##### RoHS

RoHS Compliant 6/6, Pb Free

#### Key Features

Broadcom 3008 SAS controller

8-port (internal), 12Gb/s per port

Supports 122 devices - HBA only

Automatically negotiates PCI-E (1.x, 2.x and 3.x) link width

Power management support

Supports 3.0, 6.0 and 12Gb Gb/s SAS and SATA data trans

Port independent auto-negotiation

Supports SSP, SMP, STP and SATA protocols

Zoning capability w/ SAS3 expanders

OS Support: Windows 2012, 2k8,Vista, RedHat Enterprise

Linux

Processor at 1.2 GHZ

**AOC-S3008L-L8e+** enables IPMI interface through new I<sup>2</sup>C

Uses 2 MiniSAS HD (SFF-8643) connectors

Operating Temp: 0° to 55°C

#### Dimensions and Weight

##### H x L

2.7" x 6.6"

##### Weight

0.5 lbs

#### Tested Motherboards and Servers

##### Motherboards

[X9DRH-7TF \(/products/motherboard/xeon/c600/x9drh-7t](#)

[X9DR3-LN4F+ \(/products/motherboard/xeon/c600/x9dr3-](#)

[X9DRT-PIBQ \(/products/motherboard/xeon/c600/X9DRT-](#)

[X9DRT-P \(/products/motherboard/xeon/c600/X9DRT-P.cf](#)

#### Downloads

##### User's Guide

[ [Download \(/manuals/other/AOC-S3008L-L8e.pdf\).](#)]

##### Driver

[ [Download](#)

(<https://www.supermicro.com/wdl/driver/SAS/Broadcom>

##### Firmware

[ [Download](#)

(<https://www.supermicro.com/wdl/driver/SAS/Broadcom>

]

#### Tested Hard Drives

##### Tested HDD/SSD

[ [Tested HDD List \(/en/support/resources/hdd/display?](#)

[Category=AOC&sz=3.5&ctrl=61\).](#)]



### Parts List

Certain products may not be available in your region

---

Global SKU (/en/products/SMC\_global\_skus)

---